



## Closed Loop Precise Hall Current Sensor CYHCS-LF

This Hall Effect current sensor is based on closed loop compensating principle and can be used for accurate measurement of DC and AC current, pulse currents etc. The output of the transducer reflects the real wave of the current carrying conductor.

Product Characteristics	Applications
<ul style="list-style-type: none"><li>• Excellent accuracy</li><li>• Very good linearity</li><li>• Small size and encapsulated</li><li>• Less power consumption</li><li>• Current overload capability</li></ul>	<ul style="list-style-type: none"><li>• <b>Photovoltaic equipment</b></li><li>• General Purpose Inverters</li><li>• AC/DC Variable Speed Drivers</li><li>• Battery Supplied Applications</li><li>• Uninterruptible Power Supplies (UPS)</li><li>• Switched Mode Power Supplies</li></ul>

### ELECTRICAL DATA

Part number	CYHCS-LF2000A
Nominal input current	50A ~ 2000A
Measuring range	0-50A ~ 0-3000A
Turns ratio	1:5000
Measuring resistance	with $V_c = \pm 15V$ , @ $\pm 2000A_{max}$ , 0-5.0 $\Omega$ , @ $\pm 2500A_{max}$ , 0-2.0 $\Omega$ , with $V_c = \pm 24V$ , @ $\pm 2000A_{max}$ , 0-25 $\Omega$ , @ $\pm 3000A_{max}$ , 0-10 $\Omega$ ,
Supply voltage	$\pm 15VDC \sim \pm 24VDC$
Nominal output current	10mA (for 50A) $\pm 0.2\%$ ~ 400mA (for 2000A) $\pm 0.2\%$
Accuracy at +25°C	$\pm 0.1\%$ for rated current 50A~2000A
Current consumption	$\leq 25mA$ + Output current
Galvanic isolation	50Hz, 1min, 6kV
Secondary internal resistance	$T_a = 25^\circ C$ , 28 $\Omega$

### ACCURACY DYNAMIC PERFORMANCE

Zero offset current $T_a = 25^\circ C$	$< \pm 0.2mA$
Magnetic Offset current $IP \rightarrow 0$	$< \pm 0.2mA$
Thermal drift of offset current	$IP = 0$ , $T_a = -40^\circ C \sim +85^\circ C$ , $\pm 0.5mA$
Response time	$< 1\mu s$
Accuracy	$\pm 0.2\%$ for rated current 50A~2000A
Linearity	$\leq 0.1\%FS$
Bandwidth(-3dB)	DC...150kHz
di/dt	$> 100A/\mu s$

### GENERAL DATA

Operating temperature	$-40^\circ C \sim +85^\circ C$
Storage temperature	$-40^\circ C \sim +125^\circ C$

