



Open Loop Hall Effect Current Sensor CYHCT-E2B

This Hall Effect current sensor is based on open loop principle and can be used for measurement of DC currents. The output of the transducer reflects the real wave of the current carrying conductor.

Product Characteristics	Applications
<ul style="list-style-type: none">• Excellent accuracy• Very good linearity• Small size• Light in weight• Less power consumption• Window structure• Electrically isolating the output of the transducer from the current carrying conductor• No insertion loss• Current overload capability	<ul style="list-style-type: none">• Frequency conversion timing equipments• Various power supply• Uninterruptible power supplies (UPS)• Electric welding machines• Transformer substation• Numerical controlled machine tools• Electrolyzing and electroplating equipments• Electric powered locomotive• Microcomputer monitoring• Electric power network monitoring


ELECTRICAL DATA

Part number	Measuring range	Linearity range	Overload capacity
CYHCT-E2B-10mA-XY	10mA	±20mA	200mA
CYHCT-E2B-50mA-XY	50mA	±100mA	1A
CYHCT-E2B-100mA-XY	100mA	±200mA	2A
CYHCT-E2B-200mA-XY	200mA	±400mA	4A
CYHCT-E2B-500mA-XY	500mA	±1A	10A
CYHCT-E2B-1A-XY	1A	±2A	20A
CYHCT-E2B-2A-XY	2A	±4A	40A
CYHCT-E2B-5A-XY	5A	±10A	100A
CYHCT-E2B-10A-XY	10A	±20A	200A

Nominal output voltage	Y=1 for 0-4V, Y=2 for 0-5V	V
Supply voltage	X=3 for +12V, X=4 for +15V, X=5 for +24V	V
Current consumption	≤20	mA
Galvanic isolation	3KV RMS/50Hz/min	KV

ACCURACY DYNAMIC PERFORMANCE


Zero offset voltage	±40	mV
Thermal drift of offset current	≤500	ppm/°C
Response time	≤10	µs
Accuracy	±1.0	%
Linearity	≤0.5	%FS



GENERAL DATA

Operating temperature	-10 ~ +80	°C
Storage temperature	-25 ~ +85	°C

DIMENSIONS (mm)




CONNECTION

The current carrying cable must pass through the window. The phase of output is the same as that of the current passing the window in the direction of the arrow indicated on the case.

Wiring of Terminals:

+: +15V, +12V, +24V power supply
-: NC
M: Output
G: Ground



Notes:

1. Connect the terminals of power source, outputs respectively and correctly, never make wrong connection.
2. Two potentiometers can be adjusted, only if necessary, by turning slowly to the required accuracy with a small screwdriver.
3. The best accuracy can be achieved when the window is fully filled with bus-bar (current carrying conductor).
4. The in-phase output can be obtained when the direction of current of current carrying conductor is the same as the direction of arrow marked on the transducer case.